



IN-PLANT A/C HOLIDAY DETECTOR

- HIGH VOLTAGE HOLIDAY DETECTOR
- LOW SETTING: 800v TO 8,000v
- HIGH SETTING: 3,500V TO 35,000v
- A/C POWERED (110v OR 220v)
- DIGITAL METER TO SET VOLTAGE
- LED HOLIDAY INDICATOR
- AUDIBLE PIEZO ALARM
- REMOTE INDICATOR CONNECTION



Kit includes:
Instrument
High Voltage Cable, 10'
Ground Cable, 20'
Wand and Extension Handles
Instructions

Distributed by



Easy to Read
Easy to Use
Panel !

www.teststations.com

www.detectron.com

www.tinker-rasor.com

Info@tinker-rasor.com



An ISO 9001 Registered Company

Tinker & Rasor quality is found in our products, our people and our customer service.





TINKER & RASOR

CORROSION MITIGATION INSTRUMENTATION

PRODUCT DATA SHEET

MODEL AP / AC HOLIDAY DETECTOR

Features:

- 800 volts to 35,000 volts in one unit
- Pulsing DC output voltage
- Voltage Settings 100v Resolution
- Digital meter displays voltage setting
- Regulated voltage output
- Loud and Louder volume controls
- Remote Indicator connection
- Includes cables and wands

Construction:

- Rugged Pelican® Case
- Locking instrument case
- Available in 110v or 220v AC power supply

Applications:

- Check wide variety of in-plant coatings
- Inspect for voids, pinholes, holidays, etc.

Environment:

0°C to 50°C (32°F to 122°F)

Specifications:

- 800 volts to 35,000 volts, in two steps
- 100v resolution voltage selection switch
- A/C 110v or 220v Input

Dimensions:

13.375" x 11" x 5.5"
(339.7mm x 279.4mm x 139.7mm)

Weight: 11 lbs.

(4.99 kg)

Shipping Weight: 12lbs.

(5.44 kg)

DELIVERY: 3 to 10 Working Days
F.O.B. San Gabriel, CA USA

SERVICE: **24-hour Turn-Around**

TERMS: Net30 Days, on approval of credit

WARRANTY: **90 Days**, parts and labor

MODEL APS/AC HOLIDAY DETECTOR

VOLUME SELECTION INSTRUCTIONS: Press the red cap (right) with the left or center to select the voltage. Turn the volume knob (shown above) to turn a preset. Press the red cap (right) to turn the volume knob. Press the red cap (left) to turn the volume knob. Press the red cap (right) to turn the volume knob.

VOLTAGE SELECTION

LOW SETTINGS	HIGH SETTINGS
800 (0.8 kV)	35000 (35.0 kV)
100	100
1000 (1.0 kV)	3500 (3.5 kV)
10000 (10.0 kV)	35000 (35.0 kV)

IMPORTANT: Read instructions carefully before use. **CAUTION: SHOCK HAZARD**

Very Easy panel to use

Low setting Range =
800v (.8 kV)
8,000v (8.0 kV)

High setting Range =
3,500v (3.5 kV)
35,000v (35.0 kV)

Volume Control -
Loud = ~80 dB
Louder = ~105 dB

MODEL AP / AC HOLIDAY DETECTOR

AVAILABLE AS CUSTOM ORDER